

TX-2000/TX-2100 JUMPER SETTING

- **JP1 : CMOS Select**
Pin 1-2 Short : Normal
Pin 2-3 Short : Clear CMOS
- **JP2 : For CR open/close status port selection**
Pin 1-3 、 2-4 Short: For COM1
Pin 3-5 、 4-6 Short : For COM5
- **JP3 : VGA2 12V DC SUPPLY SELECT FOR CRT**
Open VGA DSUB Pin 9 =Not Connect
Close : VGA DSUB Pin 9 =12V
- **JP4 : VGA1 12V DC SUPPLY SELECT FOR CRT**
Open VGA DSUB Pin 9 =Not Connect
Close : VGA DSUB Pin 9 =12V
- **JP5 : COM3/COM4 DC SUPPLY SELECT**
Pin 1-3 Short : COM3 Pin9 connected to 5 V DC
Pin 3-5 Short : COM3 Pin9 connected as RI
Pin 2-4 Short : COM4 Pin9 connected to 5 V DC
Pin 4-6 Short : COM4 Pin9 connected as RI
- **JP6 : COM3/COM4 DC SUPPLY SELECT**
Pin 1-3 Short : COM3 Pin1 connected to 12V
Pin 3-5 Short : COM3 Pin1 connected to DCD
Pin 2-4 Short : COM4 Pin1 connected to 12V
Pin 4-6 Short : COM4 Pin1 connected to DCD
- **JP7 : COM1/COM2 DC SUPPLY SELECT**
Pin 1-3 Short : COM1 Pin1 connected to 12V
Pin 3-5 Short : COM1 Pin1 connected to DCD
Pin 2-4 Short : COM2 Pin1 connected to 12V
Pin 4-6 Short : COM2 Pin1 connected to DCD
- **JP8 : COM1/COM1 DC SUPPLY SELECT**
Pin 1-3 Short : COM1 Pin9 connected to 5 V DC
Pin 3-5 Short : COM1 Pin9 connected as RI
Pin 2-4 Short : COM2 Pin9 connected to 5 V DC
Pin 4-6 Short : COM2 Pin9 connected as RI

